

VIBRATION RANGE

AFE SUITCASE

Suitcase-type electrical converters

The AFE suitcase-type electrical converters stand out for their reliability and versatility, allowing for the connection of multiple high-frequency needles to the same equipment.



+ Safety

The low 42V safety voltage eliminates the possibility of electric shock.




+ Reliability

Superior quality switch that disconnects the equipment when an overcurrent is detected.



+ Protective housing

Offers a double function: Shields the converter from external impacts and is simple to clean against concrete splashes.



+ Mobility

Its suitcase-style shell allows for easier transport.

- 5 meters of cable
- Voltage/frequency inputs available upon request :
 - Tri-phase: 230V 3~50Hz and 230V 3~60Hz
 - Single-phasé: 230V 3~50Hz, 230V 3~60Hz and 110V 1~60Hz

Connection possibilities

MODEL	M38	M5	M6	M7	M8
AFE 1000M P	x1	x1	x1	-	-
AFE 2000M P	x2	x2	x1	x1	x1
AFE 2000 P	x2	x2	x1	x1	x1

* Number of M-AFP ENAR pokers that can be connected at the same time to each AFE model.



Technical Data

MODEL	Weight (kg)	N° plugs	Input		Output	
			Power	Tension/Frequency	Power	Tension/Frequency
AFE 1000M P	20	1	1.3 KW 6A	230V 1 ~ 50Hz	1.0 KVA 13A	42V 3 ~ 200Hz
AFE 2000M P	29	2	2.0 KW 9A	230V 1 ~ 50Hz	1.6 KVA 23A	42V 3 ~ 200Hz
AFE 2000 P	29	2	2.8 KW 4A	400V 3 ~ 50Hz	1.6 KVA 23A	42V 3 ~ 200Hz